



## Einbauanleitung für WiiD Modchip

### Diagramme





## **Instruktionen für WiiD Modchip:**

### **Normal operation:**

Just turn on your console as normal. Wiid operation is completely transparent and will turn on only when a backup disc is inserted.

### **Firmware update:**

- Burn the firmware upgrade iso image to DVD-R/+R/-RW/+RW - Turn on the Wii console without any disc inside and go to the Disc Channel.
- Insert the firmware upgrade disc.

The disc will spin for a few seconds while the firmware is being upgraded and will finally stop. A message on the screen will say "Unable to read the disc". This is completely normal and signals that the firmware update operation has been completed.

### **Firmware recovery:**

If for any reason you want to restore your Wiid to your default factory configuration use the following procedure.

Note : wire D needs to be soldered for the recovery procedure to be effective!

- Press and hold the RESET button on your wii.
- Turn on the Wii by pressing the power button either on the Wii console or on the Wii remote while keeping the RESET button pressed.
- Wait 15 seconds and release the RESET button.

All firmware upgrades including region settings are now removed and your Wiid has been restored to the factory configuration.

### **Complete disable:**

Wiid automatically turns itself off when an original disc is inserted.

If for any reason you want to completely disable the chip use the following procedure.

Note : wire D needs to be soldered for the disable procedure to work!

- Press and hold the RESET button on your wii.
- Turn on the Wii by pressing the power button either on the Wii console or on the Wii remote while keeping the RESET button pressed.
- Wait 3 seconds and release the RESET button.

Wiid is now completely disabled.

Turn your Wii OFF and ON again to restore normal chip functionality.